

Sometimes a shutter centralisation, already wired with pilot wire, has to be radio piloted.

INSTALLATION

1. Add a R12M to the pilot wire and connect the brown wire (up movement) and the green wire (down movement) on 2 different MTR2000ER.
2. Pilot each MTR2000ER with a specific button of a radio transmitter (E2BP, TLC2C, TLC8C, etc.).
3. Configure both MTR2000ER in pulse mode.

CONFIGURATION IN PULSE MODE

On transmitter:

1. Access the Configuration Menu: **10 short presses**
2. Switch to pulse mode: **16 short presses**
Receiver confirms with a 0.5 second pulse.

IMPORTANT

- Installer configuration enabling: **23 short presses**
 Installer configuration lock: **21 short presses**

